

XUYAFPCO946S

photo-electric sensor - XUY - ampli for fibre - plastic
- 12..24VDC - M8



Main

Range of product	OsiSense XU
Series name	Application assembly
Specific application of photoelectric detector	Detection of objects on small conveyor Detection of reference and colour marks in packaging Monitoring position or presence of parts on an assembly or packing machine Use of fiber optics in vibratory environments (robot arms)
Sensor name	XUY
Sensor design	Fiber design
Emission	Red LED

Complementary

Electronic sensor type	Photo-electric sensor
Material	Plastic
Enclosure material	Polycarbonate
Pulse frequency	8 kHz
Type of output signal	Discrete
Output type	Solid state
Discrete output function	1 NO or 1 NC programmable
Discrete output type	PNP and NPN
Electrical connection	1 male connector M8, 4 pins
Cable length	2 m
Supply circuit type	DC
[Us] rated supply voltage	12...24 V DC with reverse polarity protection
Supply voltage limits	10...30 V DC
Voltage state 0 guaranteed	< 1.4 V
Voltage state 1 guaranteed	> 3 V
Switching capacity in mA	100 mA for overload and short-circuit protection
Switching frequency	< 1 kHz
Voltage drop	< 2 V (closed state)
Current consumption	<= 40 mA (no-load)
Time delay range	0.5...11 s
Delay response	<= 5 ms for plastic fibre optics 2.2 mm
Delay recovery	<= 5 ms for plastic fibre optics 2.2 mm
Setting-up	Sensitivity adjustment with teach mode
Product weight	0.056 kg

Environment

Product certifications	CE CULus
Ambient air temperature for operation	0...60 °C
Ambient air temperature for storage	-20...80 °C
Immunity to ambient light	<= 10000 lux with natural light <= 20000 lux with incandescent bulb
IP degree of protection	IP65 conforming to IEC 60529

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.